

**Mixer Amplifier with Audio Sources(MP3/TUNER/Bluetooth)  
T-60TB/T-120TB/T-240TB**



**Functions**

1. With mp3/TUNER/Bluetooth functions.
2. Apply in small places which need Public address system

**Features**

1. Standard machine cabinet design (1U), contraption, Exquisite craft, high-grade temperament.
2. With mp3/TUNER/Bluetooth module, Digital screen displaying the current music from USB.
3. With mp3/TUNER/Bluetooth remote control function.
4. 1 EMC input, 2 AUX input, 4 MIC input.
5. Channel priority: MIC1>EMC>MIC2, MIC3, AUX1, AUX2.
6. Each channel has volume control function, master volume controls and bass/treble tone control.
7. Has level indicator, overload and protection indicator.
8. With High temp, overload & short-circuit protection.
9. 2 output modes: 100V、70V (non- **Bridged mode**)
10. High energy and energy saving design of power supply and efficient power amplifier

**Specifications**

Model	T-60TB	T-120TB	T-240TB
output terminal	70V, 100V		
Output Power	60W	120W	240W
The input sensitivity and impedance	MIC1、 2、 3、 4 input:5mV/600Ω Unbalanced 6.3 connector		
	AUX1、 2 input:350mV/10KΩ Unbalanced RCA connector		
	EMC input:775mV/10KΩ Unbalanced 6.3 connector		
The output sensitivity & source impedance	MIX OUT:1000mV/470Ω Unbalanced RCA connector		
Tone	Bass: ±10dB at 100Hz Treble: ±10dB at 10KHz		
Frequency Response	50Hz~16KHz (+1dB, -3dB)		
SNR	MIC1、 2、 3:66dB; AUX1、 2:80dB		
THD	Less than 0.5%( at 1KHz, 1/3 rated power)		

Mute Control	MIC 1 has highest priority		
	and EMC has the second		
Crosstalk	≥50dB		
Heat dissipation	Cooling fan starts when amplifier turned on, infinitely variable speeds		
Protection	Over-heat, overload, short, etc		
Power Supply	~220V /50Hz		
Power consumption	100W	180W	350W
Size	484×260×44mm		
Weight	4.1Kg	4.5Kg	5.1Kg